



WarmlyYours 

Be Connected.
Be Warm. Be Radiant.

PRO-Tect

DIY Constant Wattage Heating Cable for Pipes



A burst water pipe in the dead of winter can be a huge inconvenience and completely replacing the insulation needed to prevent pipes in perimeter walls and crawlspaces from freezing can be cost-prohibitive.

To keep your most vulnerable pipes from freezing, the simple and DIY-friendly solution is to install a PRO-Tect heating cable for pipes. This 120 V plug-in heating cable generates heat (7 watts per linear foot) which will keep your pipes from freezing in low temperatures.

The integrated thermostat control, located between the non-heating lead cable and the heating wire itself, will ensure a consistent temperature while minimizing energy use.

The thermostat turns the heating cable on when exposed to temperatures below 37.4°F. It will shut the heating cable off when the pipe has been heated to a temperature of approximately 50°F.

SKU	Length	Voltage	Watts	MSRP
PTC120-7W-003	3 ft.	120 VAC	21	\$30
PTC120-7W-006	6 ft.	120 VAC	42	\$40
PTC120-7W-009	9 ft.	120 VAC	63	\$45
PTC120-7W-012	12 ft.	120 VAC	84	\$50
PTC120-7W-015	15 ft.	120 VAC	105	\$55
PTC120-7W-018	18 ft.	120 VAC	126	\$60
PTC120-7W-024	24 ft.	120 VAC	168	\$65
PTC120-7W-030	30 ft.	120 VAC	210	\$70
PTC120-7W-040	40 ft.	120 VAC	280	\$85
PTC120-7W-060	60 ft.	120 VAC	420	\$95
PTC120-7W-080	80 Ft.	120 VAC	560	\$115

Features

- Easy plug-in operation with indicator light and integrated thermostat
- Available in 3', 6', 9', 12', 15', 18', 24', 30', 40', 60', and 80' lengths
- Stops pipes from freezing at temps as low as -40°F
- 7 watts per linear foot (constant wattage)
- Safe: cUL Listed, CSA Listed, and cETLus Listed
- Voltage: 120 VAC
- Can be paired with fiberglass tape (sold separately, SKU: PT-TAPE-FG) to adhere the cable to the pipe and aluminum adhesive tape (sold separately, SKU: PT-TAPE-AL) to increase the heated contact area